

1. INSTALL 5 /8" DIA. COPPER-CLAD OR 3 /4" DIA. GALV. STEEL X 10' LONG GROUND ROD IN FOUNDATION OF EACH POLE.
2. BOND ALL FOUR ANCHOR BOLTS.
3. TERMINATE NEUTRAL AND GROUNDING CONDUCTORS ON GROUND ROD IN BASE OF FIRST POLE RECEIVING P.G.&E. SERVICE.
4. TERMINATE GROUNDING CONDUCTORS ON GROUNDING LUG IN BASE OF ALL OTHER POLES.
5. APPLICATION: 120V OR 240V OVERHEAD SERVICE FEEDING MULTIPLE STREETLIGHTS.
6. GROUND THE MESSENGER AS REQUIRED BY NATIONAL ELECTRICAL CODE.

APPROVED BY


AWJ

DATE

3/3/92

**OVERHEAD STREETLIGHT MULTIPLE
SERVICE TYPE IIC / IID - NOTES**

DEPARTMENT OF PUBLIC WORKS



DRAWING
NO.

E-45